



### Full Boar 4 Lighting Control Console

- Operating System: Hog 4 OS
- Built in DMX Processor 8000
- Built-in Kensington Security Lock
- USB Recovery Flash Drive Included
- USB Flash Drive for Show file storage included
- Desklights included
- Light Converse Visualizer dongle included
- Dust cover included
- Custom Road Case Included

### CONTROL SURFACE:

Playback Faders: 10, motorized  
GrandMaster: dedicated, motorized  
DBO Key: dedicated, toggle on/off  
Encoder Wheels: 5 with dedicated function buttons  
Function Keys: 12 keys with dedicated LCD displays  
KeyBoard: Support for external USB keyboard  
Trackball: Built-in backlit trackball with rotary encoder  
Desklight: 2, dimmable blue and white LEDs  
Worklight: Yes, dimmable white  
Ventlight: Yes, dimmable blue

### ELECTRICAL

Voltage: 100-240VAC , 50 / 60Hz  
Max Current: 4A  
Mains Connector: IEC 320

### PHYSICAL

Weight: 45 lbs (20.41 kg)  
Dimensions: 35.49" (901.19mm) wide  
22.65" (575.36mm) deep  
9.62" (244.34mm) high

### DISPLAYS

Internal: Two 15.6" widescreen touchscreens  
(both touchscreens are 10 point multi-touch )  
External: Support for two monitors / touchscreens  
(DVI-D)  
(see Hog4OS manual for list of supported touchscreens)

### DMX / ARTNET / SCAN

Local Output Processing: 12 universes (6,144 ch)  
Local DMX Outputs: 4 x Neutrik 5-pin female XLR  
Expansion via external DP8000s: Yes, Unlimited

### I/O CONNECTIVITY

USB 2.0 Ports: 4 rear  
USB 3.0 Ports: 1 top  
HogNet: Yes (allows connectivity to other consoles)  
FixtureNet: Yes (Art-Net, sACN, Visualizer connect)  
Onboard MIDI: In/Out/Thru  
(supports MIDI Show Control, MIDI Timecode , and MIDI Notes)  
Onboard LTC: Input via 3-pin XLR  
Visualizer connectivity: FixtureNet / Art-Net / sACN  
(list of supported visualizers in Hog 4 OS help manual)  
Remote Focus: Yes, via Open Sound Control

### COMPUTER

Motherboard: Advantech AIMB-581  
Processor: Intel Core i3-2120 3.3Ghz  
Memory: 8 GB  
Internal Hard Drive: 32 GB SSD  
Internal CD-R/DVD-ROM: No